Nanlite

Pavoslim 360C



Manufacturer	**Nanlite**
Type	**PAR**
DMX modes	**4**
DMX footprint	**8, 11 channels**
Beam angle	**60°**
Size (W × H × D)	**1203 × 20 × 606 mm**
GDTF fixture type	**8E823E8F-04B8-4B35-80AC-5E…**

Controls

Extra LED colours · RGB colour mixing · Colour temperature · Colour wheel · Dimmer

DMX modes

CCT+RGBW 8Bit_Reduced Channels On	8 ch
CCT+RGBW 16Bit_Reduced Channels Off	11 ch
CCT+RGBW 16Bit_Reduced Channels On	11 ch
CCT+RGBW 8Bit_Reduced Channels Off	11 ch

CCT+RGBW 8Bit_Reduced Channels On

8 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 closed 255–255 open
2	C TC	0	
3	Color RGBMagenta	0	0–10 Neutral 11–20 -150 Red 21–99 -149 > -1 Red 100–165 Neutral 166–244 1 > 149 Green 245–255 150 Green
4	Color Mix Mode	0	0–0 CCT 1–255 RGBW
5	Red	0	
6	Green	0	
7	Blue	0	
8	White	0	

CCT+RGBW 16Bit_Reduced Channels Off

11 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 closed 255–255 open
2	C TC	0	
3	Color RGBMagenta	0	0–10 Neutral 11–20 -150 Red 21–99 -149 > -1 Red 100–165 Neutral 166–244 1 > 149 Green 245–255 150 Green
4	Color Mix Mode	0	0–0 CCT 1–255 RGBW
5	Red	0	
6	Green	0	
7	Blue	0	
8	White	0	
9	Strobe Rate	0	0–3 OFF 4–4 Random Fast 5–5 Random Medium 6–6 Random Slow 7–255 0'4 > 25 Hz
10	Reserved1	0	
11	Reserved2	0	

CCT+RGBW 16Bit_Reduced Channels On

11 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 closed 255–255 open
2	C TC	0	

CCT+RGBW 16Bit_Reduced Channels On (continued)

Ch	Function	Default	DMX values
3	Color RGBMagenta	0	0–10 Neutral 11–20 -150 Red 21–99 -149 > -1 Red 100–165 Neutral 166–244 1 > 149 Green 245–255 150 Green
4	Color Mix Mode	0	0–0 CCT 1–255 RGBW
5	Red	0	
6	Green	0	
7	Blue	0	
8	White	0	
9	Strobe Rate	0	0–3 OFF 4–4 Random Fast 5–5 Random Medium 6–6 Random Slow 7–255 0'4 > 25 Hz
10	Reserved1	0	
11	Reserved2	0	

CCT+RGBW 8Bit_Reduced Channels Off

11 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 closed 255–255 open
2	C TC	0	
3	Color RGBMagenta	0	0–10 Neutral 11–20 -150 Red 21–99 -149 > -1 Red 100–165 Neutral 166–244 1 > 149 Green 245–255 150 Green
4	Color Mix Mode	0	0–0 CCT 1–255 RGBW
5	Red	0	
6	Green	0	
7	Blue	0	
8	White	0	
9	Strobe Rate	0	0–3 OFF 4–4 Random Fast 5–5 Random Medium 6–6 Random Slow 7–255 0'4 > 25 Hz
10	Reserved1	0	
11	Reserved2	0	