SHEHDS

CoralPar-C04A



Manufacturer	**SHEHDS**
Type	**PAR**
DMX modes	**2**
DMX footprint	**6, 14 channels**
Beam angle	**45°**
Size (W × H × D)	**251 × 220 × 207 mm**
GDTF fixture type	**CB538600-6D46-5149-8B0D-84…**

Controls

Extra LED colours · Effect speed · Strobe · Dimmer

Safety-relevant functions

Built-in effect programmes

DMX modes

6 Channels Mode	6 ch
14 Channels Mode	14 ch

6 Channels Mode

6 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Shutter / Strobe	0	0–8 Strobe off 9–255 Strobe 0–25 Hz
3	Color Add WW	0	
4	Color Add CW	0	
5	Effect	0	0–10 No function 11–22 Color mode ,Color controlled by CH8 23–34 Auto mode-Gradient Effect 1 35–46 Auto mode-Gradient Effect 2 47–58 Auto mode-Gradient Effect 3 59–70 Auto mode-Gradient Effect 4 71–82 Auto mode-Gradient Effect 5 83–94 Auto mode-Gradient Effect 6 95–106 Auto mode-Gradient Effect 7 107–118 Auto mode-Gradient Effect 8 119–130 Auto mode-Gradient Effect 1-8 131–142 Auto mode-Jump Effect 1 143–154 Auto mode-Jump Effect 2 155–166 Auto mode-Jump Effect 3 167–178 Auto mode-Jump Effect 4 179–190 Auto mode-Jump Effect 5 191–202 Auto mode-Jump Effect 6 203–214 Auto mode-Jump Effect 7 215–226 Auto mode-Jump Effect 8 227–238 Auto mode-Jump Effect 1-8 239–250 Auto mode-Pulse Effect 251–255 Sound mode
6	Effect Speed	0	

14 Channels Mode

14 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Shutter / Strobe	0	0–8 Strobe off 9–255 Strobe 0–25 Hz
3	Effect	0	0–10 No function 11–22 Color mode ,Color controlled by CH8 23–34 Auto mode-Gradient Effect 1 35–46 Auto mode-Gradient Effect 2 47–58 Auto mode-Gradient Effect 3 59–70 Auto mode-Gradient Effect 4 71–82 Auto mode-Gradient Effect 5 83–94 Auto mode-Gradient Effect 6 95–106 Auto mode-Gradient Effect 7 107–118 Auto mode-Gradient Effect 8 119–130 Auto mode-Gradient Effect 1-8 131–142 Auto mode-Jump Effect 1 143–154 Auto mode-Jump Effect 2 155–166 Auto mode-Jump Effect 3 167–178 Auto mode-Jump Effect 4 179–190 Auto mode-Jump Effect 5 191–202 Auto mode-Jump Effect 6 203–214 Auto mode-Jump Effect 7 215–226 Auto mode-Jump Effect 8 227–238 Auto mode-Jump Effect 1-8 239–250 Auto mode-Pulse Effect 251–255 Sound mode
4	Effect Speed	0	

14 Channels Mode (continued)

Ch	Function	Default	DMX values
5	Dimmer Mode	0	
6	Dimmer Curve	0	
7	Color Add CW	0	
8	Color Add CW	0	
9	Color Add CW	0	
10	Color Add CW	0	
11	Color Add WW	0	
12	Color Add WW	0	
13	Color Add WW	0	
14	Color Add WW	0	

Fixture model: gdtf-shehds-coralpar-c04a-2611117218
Creator: HitLight
Modifications: Original HitLight 3D housing: scripted parametric geometry modelled by HitLight from public product photos and the manufactu...