SHEHDS

LED Beam 8x12W RGBW



Manufacturer	**SHEHDS**
Type	**Moving head**
DMX modes	**2**
DMX footprint	**9, 38 channels**
Beam angle	**5°**
Tilt range	**180°**
Heads / cells	**8**
Size (W × H × D)	**1074 × 130 × 85 mm**
GDTF fixture type	**5C9B7ED3-C453-5D58-AA94-6C…**

Controls

Extra LED colours · RGB colour mixing · Effect speed · Strobe · Dimmer · Pixel control · Pan and tilt · Movement speed

Safety-relevant functions

Built-in effect programmes

DMX modes

9CH	9 ch
38CH	38 ch

9CH

9 channels

Ch	Function	Default	DMX values
1	Tilt	128	
2	Position MSpeed	0	
3	Effect	0	0–10 no effect 11–20 Built-in effect 1 21–31 Built-in effect 2 32–42 Built-in effect 3 43–53 Built-in effect 4 54–64 Built-in effect 5 65–75 Built-in effect 6 76–86 Built-in effect 7 87–97 Built-in effect 8 98–108 Built-in effect 9 109–119 Built-in effect 10 120–130 Built-in effect 11 131–141 Built-in effect 12 142–152 Built-in effect 13 153–163 Built-in effect 14 164–174 Built-in effect 15 175–185 Built-in effect 16 186–196 Built-in effect 17 197–207 Built-in effect 18 208–218 Built-in effect 19 219–229 Built-in effect 20 230–240 Built-in effect 21 241–250 Built-in effect 22 251–255 Voice control effect
4	Effect Speed	0	
5	Dimmer	0	
6	Red	0	
7	Green	0	
8	Blue	0	
9	White	0	

38CH

38 channels

Ch	Function	Default	DMX values
1	Tilt	128	
2	Position MSpeed	0	

38CH (continued)

Ch	Function	Default	DMX values
3	Effect	0	0–10 no effect 11–20 Built-in effect 1 21–31 Built-in effect 2 32–42 Built-in effect 3 43–53 Built-in effect 4 54–64 Built-in effect 5 65–75 Built-in effect 6 76–86 Built-in effect 7 87–97 Built-in effect 8 98–108 Built-in effect 9 109–119 Built-in effect 10 120–130 Built-in effect 11 131–141 Built-in effect 12 142–152 Built-in effect 13 153–163 Built-in effect 14 164–174 Built-in effect 15 175–185 Built-in effect 16 186–196 Built-in effect 17 197–207 Built-in effect 18 208–218 Built-in effect 19 219–229 Built-in effect 20 230–240 Built-in effect 21 241–250 Built-in effect 22 251–255 Voice control effect
4	Effect Speed	0	
5	Dimmer	0	
6	Shutter / Strobe	0	0–0 Strobe off (assumed) 1–255 Strobe 0–10 Hz
7	Red	0	
8	Green	0	
9	Blue	0	
10	White	0	
11	Red	0	
12	Green	0	
13	Blue	0	
14	White	0	
15	Red	0	
16	Green	0	
17	Blue	0	
18	White	0	
19	Red	0	
20	Green	0	
21	Blue	0	
22	White	0	
23	Red	0	
24	Green	0	
25	Blue	0	
26	White	0	
27	Red	0	
28	Green	0	
29	Blue	0	
30	White	0	

38CH (continued)

Ch	Function	Default	DMX values
31	Red	0	
32	Green	0	
33	Blue	0	
34	White	0	
35	Red	0	
36	Green	0	
37	Blue	0	
38	White	0	

Fixture model: gdtf-shehds-led-beam-8x12w-rgbw-202611102241
Creator: HitLight
Modifications: Original HitLight 3D housing: scripted parametric geometry modelled by HitLight from public product photos and the manufactu...