Showtec

Eventspot 1600 Q4



Manufacturer	**Showtec**
Type	**Effect light**
DMX modes	**3**
DMX footprint	**4, 6, 10 channels**
Beam angle	**10°**
Size (W × H × D)	**180 × 280 × 198 mm**
GDTF fixture type	**5CE16CF6-7CBC-4FFA-BB8B-FE…**

Controls

Extra LED colours · RGB colour mixing · Colour wheel · Effect speed · Dimmer

Safety-relevant functions

Built-in effect programmes

DMX modes

4ch	4 ch
6ch	6 ch
10ch	10 ch

4ch

4 channels

Ch	Function	Default	DMX values
1	Red	0	
2	Green	0	
3	Blue	0	
4	White	0	

6ch

6 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Strobe Mode Strobe	0	0–10 Closed 11–128 Random Slow to Fast 129–255 Pulse Slow to Fast
3	Red	0	
4	Green	0	
5	Blue	0	
6	White	0	

10ch

10 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Strobe Mode Strobe	0	0–10 Closed 11–128 Random Strobe 129–255 Pulse Strobe

10ch (continued)

Ch	Function	Default	DMX values
3	Color Wheel	0	0–7 No function (wheel slot 1) 8–13 Color 1 (wheel slot 2) 14–20 Color 2 (wheel slot 3) 21–27 Color 3 (wheel slot 4) 28–34 Color 4 (wheel slot 5) 35–41 Color 5 (wheel slot 6) 42–48 Color 6 (wheel slot 7) 49–55 Color 7 (wheel slot 8) 56–62 Color 8 (wheel slot 9) 63–69 Color 9 (wheel slot 10) 70–76 Color 10 (wheel slot 11) 77–83 Color 11 (wheel slot 12) 84–90 Color 12 (wheel slot 13) 91–97 Color 13 (wheel slot 14) 98–104 Color 14 (wheel slot 15) 105–111 Color 15 (wheel slot 16) 112–118 Color 16 (wheel slot 17) 119–125 Color 17 (wheel slot 18) 126–132 Color 18 (wheel slot 19) 133–139 Color 19 (wheel slot 20) 140–146 Color 20 (wheel slot 21) 147–153 Color 21 (wheel slot 22) 154–160 Color 22 (wheel slot 23) 161–167 Color 23 (wheel slot 24) 168–174 Color 24 (wheel slot 25) 175–181 Color 25 (wheel slot 26) 182–188 Color 26 (wheel slot 27) 189–195 Color 27 (wheel slot 28) 196–202 Color 28 (wheel slot 29) 203–209 Color 29 (wheel slot 30) 210–216 Color 30 (wheel slot 31) 217–223 Color 31 (wheel slot 32) 224–230 Color 32 (wheel slot 33) 231–255 Color 33 (wheel slot 34)
4	Effect	0	0–15 No function 16–31 Step 1 32–47 Step 2 48–63 Step 3 64–79 Step 4 80–95 Step 5 96–111 Step 6 112–127 Step 7 128–143 Step 8 144–159 Fade 1 160–175 Fade 2 176–191 Fade 3 192–207 Fade 4 208–223 Fade 5 224–239 Fade 6 240–255 Fade 7
5	Effect Speed	0	
6	Control1	0	0–15 No function 16–45 Dimmer Fast 46–75 Dimmer Slow 76–105 Linear Curve 106–135 Square Law 136–165 Inv Square Law 166–255 S Curve
7	Red	0	
8	Green	0	
9	Blue	0	

10ch (continued)

Ch	Function	Default	DMX values
10	White	0	