Showtec

Performer 2000



Manufacturer	**Showtec**
Type	**Spot**
DMX modes	**3**
DMX footprint	**1, 2, 5 channels**
Beam angle	**15-47°**
Size (W × H × D)	**30 × 122 × 84 mm**
GDTF fixture type	**530BC70D-8C7C-46B0-A344-15…**

Controls

Zoom · Strobe · Dimmer

Safety-relevant functions

Fixture reset

DMX modes

1ch	1 ch
2ch	2 ch
STDP / 5 Ch	5 ch

1ch

1 channel

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open

2ch

2 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open
2	Dimmer Fine	0	Fine byte of Dimmer

STDP / 5 Ch

5 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open
2	Dimmer Mode	0	
3	Shutter / Strobe	9	0–9 Open 10–99 Strobe · Slow - Fast 100–109 Open 110–179 Pulse Slow - Fast 180–189 Open 190–255 Random Slow - Fast
4	Zoom	127	
5	Function	0	0–200 No Function 201–220 Motor Reset 221–255 No Function