Showtec

Performer Profile Zoom 150 Q6



Manufacturer	**Showtec**
Type	**Profile spot**
DMX modes	**1**
DMX footprint	**20 channels**
Beam angle	**37.5°**
Size (W × H × D)	**196 × 569 × 222 mm**
GDTF fixture type	**4A28C9B9-6B32-4174-B1A4-2B…**

Controls

Extra LED colours · RGB colour mixing · Colour temperature · Colour wheel · Effect speed · Dimmer

Safety-relevant functions

Built-in effect programmes

DMX modes

20ch TR16	20 ch

20ch TR16

20 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Dimmer Fine	0	Fine byte of Dimmer
3	Red	255	
4	Red Fine	255	Fine byte of Red
5	Green	255	
6	Green Fine	255	Fine byte of Green
7	Blue	255	
8	Blue Fine	255	Fine byte of Blue
9	Amber	255	
10	Amber Fine	255	Fine byte of Amber
11	Color Add L	255	
12	Color Add L Fine	255	Fine byte of Color Add L
13	Color Add C	255	
14	Color Add C Fine	255	Fine byte of Color Add C
15	Color Preset	0	0–10 NoFunction 11–250 ColorPresets 251–255 NoFunctionEnd
16	C TC	0	0–9 NoFunction 10–255 CCT1800to10000K
17	Effect	0	0–40 NoFunction 41–50 Auto1 51–60 Auto2 61–70 Auto3 71–80 Auto4 81–90 Auto5 91–100 Auto6 101–110 Auto7 111–120 Auto8 121–130 Auto9 131–140 Auto10 141–150 CustomProgram1 151–160 CustomProgram2 161–255 NoFunctionEnd
18	Effect Speed	0	
19	Shutter1Strobe	0	0–9 NoFunction 10–99 Strobe 100–109 NoFunction2 110–179 LightningStrobe 180–189 NoFunction3 190–255 RandomStrobe

20ch TR16 (continued)

Ch	Function	Default	DMX values
20	Control1	0	0–10 NoFunction 11–60 Reserved1 61–70 LiveMode 71–80 StudioMode 81–90 PowerMode 91–100 Reserved2 101–110 DimmerLinear 111–120 DimmerMode4 121–150 Reserved3 151–160 PWM1200Hz 161–170 PWM2400Hz 171–180 PWM4000Hz 181–190 PWM6000Hz 191–200 PWM25000Hz 201–210 AllReset 211–255 Reserved4