Snow Lighting

SnowPar Pro Tri 18



Manufacturer	**Snow Lighting**
Type	**PAR**
DMX modes	**4**
DMX footprint	**1, 4, 6 channels**
Beam angle	**25°**
Size (W × H × D)	**260 × 195 × 45 mm**
GDTF fixture type	**67032405-C5FC-49F3-97BD-D8…**

Controls

RGB colour mixing · Colour wheel · Strobe · Dimmer

Safety-relevant functions

Strobe

DMX modes

1Ch Mode	1 ch
3Ch Mode	4 ch
4Ch Mode	4 ch
6Ch mode	6 ch

1Ch Mode

1 channel

Ch	Function	Default	DMX values
1	Color Effects1	0	0–17 Black 18–35 Red 36–53 Green 54–71 Blue 72–89 Amber 90–107 Orange 108–125 Yellow 126–143 Purple 144–161 Pink 162–179 Cyan 180–197 Light red 198–215 Light green 216–233 Light blue 234–251 Warm white 252–255 Cold white

3Ch Mode

4 channels

Ch	Function	Default	DMX values
1	Reserved 1	0	
2	Color RGBRed	255	
3	Color RGBGreen	255	
4	Color RGBBlue	255	

4Ch Mode

4 channels

Ch	Function	Default	DMX values
1	Dimmer	255	0–254 Closed 255–255 Open
2	Color RGBRed	255	
3	Color RGBGreen	255	
4	Color RGBBlue	255	

6Ch mode

6 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open
2	Color RGBRed	255	
3	Color RGBGreen	255	
4	Color RGBBlue	255	
5	Shutter / Strobe	0	0–0 Open 1–255 Strobe
6	Color Effects1	0	0–0 Open 1–27 Program 1 28–55 Program 2 56–83 Program 3 84–111 Program 4 112–139 Program 5 140–167 Program 6 168–195 Program 7 196–223 Program 8 224–251 Program 9 252–255 Sound