Stage4

LEDBlinder 200



Manufacturer	**Stage4**
Type	**Blinder**
DMX modes	**4**
DMX footprint	**1, 2, 4, 11 channels**
Beam angle	**33°**
Size (W × H × D)	**375 × 170 × 45 mm**
GDTF fixture type	**F7A9556E-4797-481A-814F-98…**

Controls

Extra LED colours · Effect speed · Dimmer

Safety-relevant functions

Strobe · Built-in effect programmes

DMX modes

1 DMX	1 ch
2 DMX	2 ch
4 DMX	4 ch
11 DMX	11 ch

1 DMX

1 channel

Ch	Function	Default	DMX values
1	Dimmer	0	

2 DMX

2 channels

Ch	Function	Default	DMX values
1	Color Add WW	0	
2	Color Add WW	0	

4 DMX

4 channels

Ch	Function	Default	DMX values
1	Color Add WW	0	
2	Color Add WW	0	
3	Color Add CW	0	
4	Color Add CW	0	

11 DMX

11 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open
2	Color Add CW	0	
3	Color Add CW	0	
4	Color Add WW	0	
5	Color Add WW	0	
6	Shutter / Strobe	0	
7	Shutter1Strobe	0	
8	Dimmer Curve	0	0–5 No Func 6–63 Linear 64–127 Square 128–191 Inv Square 192–255 S-Curve
9	Intensity MSpeed	0	0–5 No Func 6–50 Delay 0_1s 51–100 Delay 0_2s 101–150 Delay 0_5s 151–200 Delay 1s 201–255 Delay 1_5s
10	Effect	0	0–50 No Func 51–100 Colour 101–150 Step 151–200 Fade 201–250 Auto 251–255 Sound
11	Effect Speed	0	