Stage4

REPAR COB200 CW



Manufacturer	**Stage4**
Type	**Effect light**
DMX modes	**2**
DMX footprint	**3, 6 channels**
Beam angle	**25°**
Size (W × H × D)	**250 × 180 × 33 mm**
GDTF fixture type	**3CB14BD4-26B7-41F9-BBE7-86…**

Controls

Extra LED colours · Effect speed · Dimmer

Safety-relevant functions

Built-in effect programmes

DMX modes

3 DMX	3 ch
6 DMX	6 ch

3 DMX

3 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open
2	Color Add CW	0	
3	Color Add WW	0	

6 DMX

6 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open
2	Strobe Mode Strobe	0	
3	Color Add CW	0	
4	Color Add WW	0	
5	Effect	0	0–4 No Func 5–80 Step 81–150 Fade 151–255 Sound
6	Effect Speed	0	