stagetronix

LED Par WW Light



Manufacturer	**stagetronix**
Type	**Effect light**
DMX modes	**1**
DMX footprint	**8 channels**
Beam angle	**24-110°**
Size (W × H × D)	**218 × 68 × 131 mm**
GDTF fixture type	**3D7F9688-FCBE-44F4-A70D-0F…**

Controls

Extra LED colours · RGB colour mixing · Effect speed · Strobe · Dimmer

Safety-relevant functions

Strobe · Built-in effect programmes

DMX modes

Standard	8 ch

Standard

8 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–63 Closed 64–127 25% 128–191 50% 192–254 75% 255–255 Open
2	Shutter / Strobe	3	
3	Effect	0	20–39 DMX 8CH Control 40–59 Different Colors Output 60–79 Colors Jump Change 80–99 Colors Gradate 100–119 Colors Pulse Change 120–255 Sound Active
4	Effect Speed	128	
5	Red	255	0–63 Min 64–127 25% 128–191 50% 192–254 75% 255–255 Max
6	Green	255	0–63 Min 64–127 25% 128–191 50% 192–254 75% 255–255 Max
7	Blue	255	0–63 Min 64–127 25% 128–191 50% 192–254 75% 255–255 Max
8	White	255	0–63 Min 64–127 25% 128–191 50% 192–254 75% 255–255 Max