Terbly

F90-WW



Manufacturer	**Terbly**
Type	**Spot**
DMX modes	**3**
DMX footprint	**2, 3, 6 channels**
Beam angle	**15-57°**
Size (W × H × D)	**349 × 666 × 349 mm**
GDTF fixture type	**B2884E23-82D8-4564-9EB6-1C…**

Controls

Zoom · Extra LED colours · Dimmer

DMX modes

2Channel	2 ch
3Channel	3 ch
6Channel	6 ch

2Channel

2 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open
2	Zoom	128	0–127 narrow 128–254 normal 255–255 wide

3Channel

3 channels

Ch	Function	Default	DMX values
1	Color Add WW	255	
2	Dimmer	0	0–254 Closed 255–255 Open
3	Zoom	128	0–127 narrow 128–254 normal 255–255 wide

6Channel

6 channels

Ch	Function	Default	DMX values
1	Color Add WW	255	
2	Dimmer	0	0–254 Closed 255–255 Open
3	Dimmer Fine	0	Fine byte of Dimmer
4	Zoom	128	0–127 narrow 128–254 normal 255–255 wide
5	Zoom Fine	0	Fine byte of Zoom
6	Dimmer Curve	0	0–20 Standard 21–40 Stage 41–60 TV 61–80 Architectural 81–100 Theatre 101–255 Default to Unit Curve Setting