Terbly

OVAL60D



Manufacturer	**Terbly**
Type	**PAR**
DMX modes	**4**
DMX footprint	**5, 6, 8, 10 channels**
Beam angle	**12°**
Size (W × H × D)	**269 × 292 × 232 mm**
GDTF fixture type	**CFCB05D6-A3AF-4195-8EE6-D0…**

Controls

Extra LED colours · RGB colour mixing · Colour temperature · Colour wheel · Strobe · Dimmer

Safety-relevant functions

Built-in effect programmes

DMX modes

5 Channel	5 ch
6 Channel	6 ch
8 Channel	8 ch
10 Channel	10 ch

5 Channel

5 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	0	
5	Color Add RY	0	

6 Channel

6 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	0	
5	Color Add RY	0	
6	Dimmer	0	0–254 Closed 255–255 Open

8 Channel

8 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	0	
5	Color Add RY	0	
6	C TO	0	0–0 No function 1–254 2700K 255–255 7200K

8 Channel (continued)

Ch	Function	Default	DMX values
7	Color Macro1	0	0–0 No function 1–7 Macro 1 8–15 Macro 2 16–23 Macro 3 24–31 Macro 4 32–39 Macro 5 40–47 Macro 6 48–55 Macro 7 56–63 Macro 8 64–71 Macro 9 72–79 Macro 10 80–87 Macro 11 88–95 Macro 12 96–103 Macro 13 104–111 Macro 14 112–119 Macro 15 120–127 Macro 16 128–135 Macro 17 136–143 Macro 18 144–151 Macro 19 152–159 Macro 20 160–167 Macro 21 168–175 Macro 22 176–183 Macro 23 184–191 Macro 24 192–199 Macro 25 200–207 Macro 26 208–215 Macro 27 216–223 Macro 28 224–231 Macro 29 232–239 Macro 30 240–247 Macro 31 248–255 Macro 32
8	Dimmer	0	0–254 Closed 255–255 Open

10 Channel

10 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	0	
5	Color Add RY	0	
6	C TO	0	0–0 No function 1–254 2700K 255–255 7200K

10 Channel (continued)

Ch	Function	Default	DMX values
7	Color Macro1	0	0–0 No function 1–7 Macro 1 8–15 Macro 2 16–23 Macro 3 24–31 Macro 4 32–39 Macro 5 40–47 Macro 6 48–55 Macro 7 56–63 Macro 8 64–71 Macro 9 72–79 Macro 10 80–87 Macro 11 88–95 Macro 12 96–103 Macro 13 104–111 Macro 14 112–119 Macro 15 120–127 Macro 16 128–135 Macro 17 136–143 Macro 18 144–151 Macro 19 152–159 Macro 20 160–167 Macro 21 168–175 Macro 22 176–183 Macro 23 184–191 Macro 24 192–199 Macro 25 200–207 Macro 26 208–215 Macro 27 216–223 Macro 28 224–231 Macro 29 232–239 Macro 30 240–247 Macro 31 248–255 Macro 32
8	Color Control	0	0–10 No function 11–40 Internal program 1 41–70 Internal program 2 71–100 Internal program 3 101–130 Internal program 4 131–160 Internal program 5 161–190 Internal program 6 191–220 Internal program 7 221–255 Gradient effect
9	Shutter / Strobe	63	0–31 Closed 32–63 Open 64–94 min Strobe 95–95 max Strobe 96–127 Open 2 128–158 min Pulse 159–159 max Pulse 160–191 Open 3 192–222 Random · min Rnd 1–24.2 Hz 223–223 Random · maxRnd 25 Hz 224–255 Open 4
10	Dimmer	0	0–254 Closed 255–255 Open