Terbly

T400WW



Manufacturer	**Terbly**
Type	**Spot**
DMX modes	**2**
DMX footprint	**1, 4 channels**
Beam angle	**15°**
Size (W × H × D)	**208 × 786 × 215 mm**
GDTF fixture type	**E0052CB4-B1D7-468C-B087-2A…**

Controls

Strobe · Dimmer

DMX modes

1Channel	1 ch
4 Channel	4 ch

1Channel

1 channel

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open

4 Channel

4 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open
2	Dimmer Fine	0	Fine byte of Dimmer
3	Shutter / Strobe	20	0–10 Closed 11–20 Open 21–116 min Strobe 117–117 max Strobe 118–126 Open 2 127–179 min Pulse 180–180 max Pulse 181–191 Open 3 192–244 Random · min Rnd 1–24.5 Hz 245–245 Random · max Rnd 25 Hz 246–255 Open 4
4	Dimmer Curve	0	0–20 Standard 21–40 Stage 41–60 TV 61–80 Architectural 81–100 Theatre 101–255 Default to Unit Setting