Wisdom

Strobe RGB 1000W



Manufacturer	**Wisdom**
Type	**Strobe**
DMX modes	**3**
DMX footprint	**6, 16, 19 channels**
Beam angle	**25°**
Heads / cells	**2**
Size (W × H × D)	**420 × 150 × 200 mm**
GDTF fixture type	**997287AE-58F1-449C-9E9A-798…**

Controls

RGB colour mixing · Colour wheel · Strobe · Dimmer · Pixel control

Safety-relevant functions

Strobe

DMX modes

6ch	6 ch
16ch	16 ch
31ch	19 ch

6ch

6 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Strobe Mode Shutter	255	
3	Shutter / Strobe	0	
4	Red	255	
5	Green	255	
6	Blue	255	

16ch

16 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Strobe Mode Shutter	255	
3	Shutter / Strobe	0	
4	Red	255	
5	Green	255	
6	Blue	255	
7	Color1Mode	0	
8	Color Wheel	0	
9	Color Macro1	0	
10	Color Macro1Rate	0	
11	Color Macro2	0	
12	Color Macro2Rate	0	
13	Color Macro3	0	
14	Color Macro3Rate	0	
15	Color Macro4	0	
16	Color Macro4Rate	0	

31ch

19 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Strobe Mode Shutter	255	
3	Shutter / Strobe	0	
4	Dummy	0	
5	Dummy	0	
6	Dummy	0	
7	Color1Mode	0	
8	Color Wheel	0	
9	Color Macro1	0	
10	Color Macro1Rate	0	
11	Color Macro2	0	
12	Color Macro2Rate	0	
13	Color Macro3	0	
14	Color Macro3Rate	0	
15	Color Macro4	0	
16	Color Macro4Rate	0	

31ch (continued)

Ch	Function	Default	DMX values
17	Red	255	
18	Green	255	
19	Blue	255	